

MB-3790 Instruction Manual



*Please read the instruction manual carefully before use


Specifications :

Capacity	4000mAh
Input	Micro USB DC 5V 2A
Output 1	USB DC 5V 2A
Product size	126.3*66*10.8(mm)
Product net weight	120.0(g)
Full charging time	3 (hours)
Operation temperature	-10~45(°C)
Battery type	Li-polymer

Features:

- Solar panel: 160mA.
- Size of your smartphone
- Ultra slim 10.8mm.
- 5 Led indicators to show battery level and status, the first LED indicate solar charging status.
- Short circuit, over-discharge, over-charge protection designed in PCBA

Product presentation :



1. Monocrystalline Solar Panel.
2. USB Output Port.
3. Power Switch.
4. LED Indicators.
5. Micro USB Input Port.

Accessory List: Manual, USB charging cable, Power bank.

Operating instructions:

To collect and store solar power to the Solar Charger's internal battery:

- Place the power bank in direct sunlight; make sure the embedded solar panel is positioned towards the sun.

Note: Kindly note that the solar panel is designed for emergency charging. It should not be the primary source of charging. Prolonged exposure under the burning sun will cause damage to the solar panel.

- The first LED light will be on when the power bank is getting charged under the sunlight.

Charging the Power bank from an external power source:

- Plug in the included USB cable to a power source such as an AC power adapter or any other USB power source (i.e. Computer).
- Battery's charging status is indicated by 5 LED light indicators in the following manner:

Charging Status LED Indicators	0%~25%	25%~50%	50%~75%	75%~99%	100%
1st	Flashing Blue	•	•	•	•
2nd	OFF	Flashing Blue	•	•	•
3rd	OFF	OFF	Flashing Blue	•	•
4th	OFF	OFF	OFF	Flashing Blue	•
5th	• when it is under solar charged, green light is flashing				

• Solid Blue.

- LED indicators will be constant on after the power bank is fully charged.
- An external power source takes approximately 3 hours to fully charge the power bank.

Charging other devices:

- Press the power button to turn the power bank on.
- Connect the device to the USB port using the appropriate charging cable. It starts charging the device.
- The device will start charging.
- Keep pressing ON/OFF Switch to turn off the power bank.

Note: When the power bank is in use and the capacity is less than 2%, the power bank will automatically shut off to avoid over discharge of the battery.

*The Solar Power Bank will be turn off automatically when you do not use it.

NOTE:

- Do not attempt to open or disassemble the power bank.
- Do not use this power bank in the environment that the temperature is higher than 45°C or lower than -10°C.
- Do not allow children to play with the power bank.
- Do not throw the power bank into the fire.
- Stop using this power bank if the product temperature is too high.
- When fully charged, unplug the power cord.

Distributed by : Electus Distribution , Tel : 1300738555 , www.electusdistribution.com.au