

USB To RS-422 / 485 Converter

XC4132



Ø USB

- 2 Chipset : Silicon Laboratories CP2102
- 2 Compliant : USB 1.0 , 1.1 , 2.0
- 2 Connector : USB type A
- 2 Baud Rates : Full speed 12 Mbps

Ø Serial Port

- 2 Port: 1 port (Terminal Block)
- 2 RS-422 : RxD+ , RxD- , TxD+ , TxD- ,
- 2 RS-485 : Data+ , Data-
- 2 RS-422 , RS-485 Auto Detect
- 2 RS-422 , RS-485 Surge Protect
- 2 Receive buffer : 576 Byte
- 2 Transmit buffer : 640 Byte
- 2 Baud Rate : 300 ~ 230.4 K bps
- 2 Flow Control : X-On / X-Off or Hardware

Ø Driver Support

- 2 Windows-98SE/2000/XP/Server 2003/Vista/Win-7/Mac osx/os9/Linux 2.4/2.6

Ø Power : USB Bus Power (5V)

Ø Dimension

- 2 Size : 55 x 40 x 25 mm (W x D x H)
- 2 Weight : 35 gm

Ø Environment

- 2 Operating Temp : 0~60°C
- 2 Storage Temp : -20 to 85°C
- 2 Humidity : 5~95 % RH

