


2 Pin LED Strip Connector to 2.1mm DC Socket




Connection:


1. Cut the desired length of the LED strip ensuring that the current rating doesn't exceed 4A(12V), 2A(24V).




2. Open the 2 pin clip on connector.



3. Insert the LED strip into the connector and ensure that the contacts slide directly in line with the 2 pins. The correct polarity positive and negative will also need to match with the LED strip.



4. Close the connector securely in place. Now you can connect a 12VDC or 24VDC mains power adaptor into the 2.1mm DC socket.



Specifications:

Voltage: 12/24VDC

Current: 4A (12V)

2A (24V)

LED Type: 5050/5060

LED Colour: Single 2 Pin

LED Strip Width: 10mm

Dimensions: 161(L)mm