



DIGITECH
Audio



**Rechargeable Wireless
Stereo Headphones
with Digital Decoding
AA-2036
User Manual**

OPERATING INSTRUCTIONS

1. Insert the Power Adaptor into the 100-240VAC socket. Then connect the 3.5mm plug of the Power Adaptor with the DC5V outlet hole on the transmitter. If the power light turns blue, the transmitter is linked to the power correctly. The transmitter also has the function of charge. When switched OFF, Audio light will not work. See below Pictures.



2. Connect one end of the audio cable with 3.5mm to the audio output socket of the hi-fi audio equipment (such as TV, DVD, MP3/MP4, PC or Mobile). Connect the other end of the cable to the audio-in on transmitter. The audio light will turn blue if your hi-fi equipment begins to input the signal of audio to the transmitter. At the same time you should put the button to switch power on, and audio light is red standby if after around 5 minutes without audio signal input, Audio light blue and transmitter open when audio signal input. See below picture for reference.

3. Turn on the power button of the receiver (headphone built-in 800mAh rechargeable Li-ion battery), and the receiver can receive the signal of audio from the transmitter (if the power transmitter cradle work well) while the right indicating light turn blue, if receiver doesn't receive any signal, the light will turn to red. Please see the below image for reference.



4. In the case of normal listening to music, remove the 3.5mm audio cable, and plug in optical fibers. Optical fibers another head is connected with any audio source you want. Start playing music you love, at this time if again with 3.5mm audio cable, automatically switch to 3.5 audio source, if need optical fiber play music, just remove the 3.5mm audio source. If you would like to use as a wired headphone is available, just put the headphone plug in 3.5mm audio cable, another head connect with 3.5mm audio interface.



5. According to your different requirement to adjust the voice volume (press the VOL+ or VOL-)



6. As the Li-battery power low 2.7V (it was not enough to use, at this moment the receiver can protect the Li-battery by turning off power and conducting the low voltage) , put the receiver in the corresponding receiver charging slot position ,the charging place of the receiver on the needle of transmitter then the receiver will shut down automatically, at this time, the transmitter can charge the receiver automatically, The power light will turn red while charging, the power light turn blue when the receiver fully charged (Before using the first best charging 6 to 10 hours).



NOTICE

1. Avoid exposure to high temperature and humid environments.
2. When not in use for long periods of time, ensure the receiver is charged once every 3-6 months. This will help to protect battery life.
3. Receiver to the right of audio jack is used as a wired headphone. With a 3.5mm audio cable connect with TV, DVD, MP3/MP4, PC or Mobile, etc., the other end of the 3.5mm audio line connects with the receiver on the right side of the Audio jack and can be used as a wired headphone. Without shutdown using a 3.5mm audio cable connect with the receiver on the right side of audio-in socket hold, which will disconnect with the wireless receiver. In order to save electricity click the shutdown button when used as a wired headphone.
4. If headphones are not paired to the transmitter on first operation, turn on the power of transmitter and receiver and press on the headphone switches, then the light will turn red on the left side of the receiver, the audio light will turn blue. With both hands hold the scan button of headphones and transmitter at the same time, the signal indicator lights of receiver and transmitter blink until headphones makes a sound. The headphones should now be paired to the transmitter.
6. Check that the headphones are not set to maximum volume before using in order to avoid damaging your hearing.
7. Be careful to pay attention to the outside world when using headphones.

BOX CONTENTS

1 x Rechargeable Wireless Stereo Headphones
1 x Transmitter
1 x 3.5mm Cable
1 x 3.5mm to RCA Adaptor Cable
1 x TOSLINK Cable
1 x Power Supply

SPECIFICATIONS

Inputs: 1 x 3.5mm, 1 x Optical

Power: 5VDC @ 500mA

Battery: 2.7V 800mAh Li-ion Rechargeable

Weight:

Headphones: 242g

Transmitter: 226g

Dimensions:

Headphones: 200(W) x 190(H) x 74(D)mm

Transmitter: 235(H) x 112(Dia.)mm



Distributed by:
TechBrands by Electus Distribution Pty. Ltd.
320 Victoria Rd, Rydalmere
NSW 2116 Australia

Ph: 1300 738 555
Int'l: +61 2 8832 3200
Fax: 1300 738 500

www.techbrands.com

Made in China