digitech

Digital Pay TV

Remote Control

Model: AR1737

Instruction Manual

Introduction

The Pay TV Remote will enable you to:

1. Operate your Pay TV Service
2. Control the main functions of your television
3. Control other pieces of audio/visual equipment connected to your Pay TV Service

This Advanced User Guide will provide you with easy-to-understand instructions on how to use the Pay TV Remote to control your television/audio/visual device by inputting Device Codes into the Pay TV Remote. These codes are provided in the back of this Guide. This will enable the Pay TV Remote to control almost any device!

If your device brand is not included or you are having difficulty entering the codes, you can "learn" them from your Pay TV Remote.

Note: For information on using the Pay TV Remote to operate the Pay TV Service, refer to the "Pay TV Guide" which is available from

Batteries

The Pay TV Remote requires 2 new AA (LR6, UM3) alkaline batteries, when the batteries need replacing a message will appear on the Pay TV Service and a battery low symbol will be in the i-Search banner.

To change the batteries:

1. Remove the battery cover by pushing back the catch at the bottom of the Pay TV Remote and then lift off the cover.

2. Remove the old batteries

3. Install two fresh AA (LR6, UM3) alkaline batteries as indicated by the illustration in the battery compartment. Be sure to match the + and - marks on the batteries to their respective marks inside the battery compartment.

4. Replace the battery cover by inserting the tabs at the top of the battery cover first, then pushing the cover into place.

Do not leave flat batteries in your Pay TV Remote.

Do not mix different battery types, e.g. Alkaline and Manganese.

Do not mix old and new batteries – replace both batteries at the same time

Dispose of flat batteries in an environmentally-friendly way

Pay TV Remote



Pay TV
Takes you from the TV Guide (or any FOXTEL menu screen) to the last channel you were watching

av
Switches to 'AV mode'

on demand
to access On Demand programmes and Optus Pay TV Box Office titles

tv guide
Displays your Pay TV Guide's programme listings screen

setup
Displays the Setup screen where you can change the FOXTEL i32 settings

vol + and –
Changes the volume up or down

mute
Turns the sound on or off

colour buttons
Use to select the operating colour option shown on screen

transport buttons
The REW, PAUSE (top part of key) / PLAY (bottom part of key), FF, REC and STOP keys operate the transport functions (PLAY, FF, REW etc.) on your device.

red colour button
Launches an active service when you see the red button on your TV screen

number buttons (0–9)
Use to change channel, enter numbers and select on-screen options

i-search
Launches an active service when you see the red button on your TV screen

i-Navigator
Moves the i-Navigator around the screen

select
Confirms a choice or makes a selection. Also displays the i-Search banner

help
Takes you instantly to the FOXTEL Help Channel, regardless of what channel or menu you are viewing

back
Jumps back to the previous screen you were browsing or the previous channel you were watching

Using the Pay TV Remote with the Pay TV Guide

You can use the following buttons on the Pay TV Remote to perform the following functions on the Pay TV Service



- To display any section of the Pay TV Guide, press the corresponding button on your Pay TV Remote, e.g. for example, to display Pay TV On Demand, press on demand.

- Use the **arrows** to move the highlight around the screen, then to choose the highlighted item, press **select**

- On many of the Pay TV Guide screens, you use the colour buttons to choose options or change the display. When a colour button is displayed next to an option, press the same colour button on your Pay TV Remote to choose that option.

- Press the **number** buttons to enter numbers on the screen. You can also use the **number** buttons as a short-cut, whenever a numbered list is shown. You can use the **number** buttons to write the letters and symbols marked on the buttons onto the screen.

  Press the button once for the first letter, and again for the next letter. When the letter you want is displayed (similar to sending text messages with your mobile phone).

- To see information about a highlighted programme, press **i**

- To exit any screen, without saving any changes, and go back to the previous Pay TV Guide screen, press **back**.

- When full screens of listings are displayed, you can press the **ch +** to 'page up' and 'page down' a full screen of listings.

- To return to the channel you were last watching, press **Pay TV**



Using the Pay TV Remote control to record and watch programmes

The buttons on your Pay TV Remote that you use to record and watch programmes are located in the centre of the Pay TV Remote and are described below. These buttons can be used in the same way in various places, for example, you can press the **REC** key to record while you are watching TV, or when a programme is highlighted in the F Pay TV Guide, Pay TV On Demand or Personal Planner.

- To record a programme, press the **REC key.**

- To rewind a programme, press rewind (◀◀).

- To pause a programme or start a 'Live Pause' recording, press pause (❚❚).

- To play a recorded programme, or restart a paused programme, press play (▶).

- To fast forward a programme, press fast forward (▶▶).

- To stop playback of a programme, press stop (■).

AV Mode of the Pay TV Remote

Pressing the av button on the Pay TV remote allows:

- The Pay TV to route the input from the VCR SCART connector on the back of the Pay TV to the output of the primary or TV SCART.
  In practice this means your VCR (or DVD Recorder) should be connected to the Pay TV Receiver and your TV set on the Pay TV. Pressing the av button displays the VCR's output on the television. If nothing is connected to the VCR SCART on the Pay TV then pressing the av button on the Pay TV Remote blanks the television screen

- In AV mode the Pay TV Remote buttons are disabled unless it has been programmed as shown in this guide (or unless it has been learned from your television's or other device's functions)

To identify which of the two SCART connectors is the VCR SCART look at the back of the Pay TV, the VCR SCART will be the left SCART connector and marked VCR SCART

Using the av button with a loop-through device

You may wish to connect more items of equipment to your television than your television has connectors to support. For example, a Pay TV, plus a VCR, DVD player and/or games console). In this circumstance the Pay TV can act as an AV switcher allowing the television connector used by the Pay TV to be shared with another item of equipment. This item is referred to as the "loop-through device". The loop-through device is the VCR which connects at the back of the Pay TV rather than directly to the television (see diagram on previous page). Usually this device is the VCR.

If you have a "loop-through device" you use the av button on the Pay TV Remote to switch between the Pay TV services and the loop-through device.

1. To switch to the looped-through device, press the av button on the Pay TV Remote.

Once you have pressed the av button, all the buttons on the Pay TV Remote are disabled (unless it has been programmed as shown in this Guide, in which case it will control your television's volume, mute and power, except Pay TV and the Pay TV Guide buttons (tv guide, on demand, active and planner)

2. To return to Pay TV, press Pay TV (or any of the Pay TV Guide buttons)

- If you want to use the 'loop-through' facility, your television must be connected to the Pay TV SCART connector on the Pay TV via the loop-through unit (e.g. VCR) must be connected to the VCR SCART connector on the Pay TV and the Video Output for the i922 must be set to PAL.

- If your set-top does not include a looped-through device, then when you press the av button on the Pay TV Remote, your television will display a blank screen when the av button is pressed. To return to Pay TV press the Pay TV button.

- The AV switching function of the Pay TV switches audio and composite video only.

- Loop-through routes the VCR SCART input through to the TV SCART output. Loop-through does not affect the HDMI or HD Component outputs

Pay TV Remote Functions in AV mode

When in AV mode with a Device Code programmed into the Pay TV Remote the buttons perform the following functions

1. Power
  The Power button will operate the Power or Standby function on your programmed device
2. Play
  Switches the Pay TV Remote back to Pay TV mode and allows the Pay TV service to override any loop-through device and displays the Pay TV service.
3. tv guide
  Switches the Pay TV Remote back to Pay TV mode and allows the Pay TV service to override any loop-through device and displays the Pay TV Guide.
4. on demand
  Switches the Pay TV Remote back to Pay TV mode and allows the Pay TV service to override any loop-through device and displays the Pay TV active.
5. active
  Switches the Pay TV Remote back to Pay TV mode and allows the Pay TV service to override any loop-through device and displays the Pay TV Active menu.
6. i-Planner
  Switches the Pay TV Remote back to Pay TV mode and allows the Pay TV service to override any loop-through device and displays the Pay TV Planner.
7. i-Setup
  The setup button has no function and is therefore available for learning (see page 14).
8. Menu
  Provides the Menu function in DVD / VCR mode.
9. Arrows, select and back
  These buttons are provided for Menu control in DVD / VCR mode.
  The Select button is provided to switch your television on
  If you cannot control your device properly, please continue the search Method, as you may be using the wrong code.
10. Volume +/-
  Change the volume on the programmed device (television or amp/tuner, depending on programmed device).
11. Channel +/-
  Change channel on the programmed device (television or VCR/DVD depending on programmed device).
12. mute
  Mutes the volume on the programmed devices (television or amp/tuner, depending on programmed device).
13. help
  Acts as an AV button does on your television's Remote Control, switches to AV mode and displays on the television
14. Transport buttons
  The REW, PAUSE (top part of key) / PLAY (bottom part of key), FF, REC and STOP keys operate the transport functions (PLAY, FF, REW etc.) of your DVD / VCR.
15. Number Buttons
  The Number buttons (0 - 9) change channel on the your television.
16. Colour Buttons
  Red: VCR input selection on amp/tuner.
  Green: DAT input selection on amp/tuner.
  Yellow: TV input selection on amp/tuner.
  Blue: Input select toggle feature on amp/tuner.

Note: not all the above functions are supported for all Devices in the Code library.

Setting the Code for your Device

Setting the Code for Your Television

1. Switch your television on (not on standby).
2. Find your device Code in the Television Code Reference section (page 25 - 42). Codes are listed by brand name, with the most common Code is listed first.
3. Press and release the av button on the Pay TV Remote.
4. Press and hold the **select** button, then press and hold the **1** button. Keep both buttons held down until the LED on the Pay TV Remote flashes twice.
5. Now enter your 4-digit Code, using the **number** buttons. The LED will flash twice to indicate that the Code has been accepted
6. Point the Pay TV Remote towards your television and press the Power button. If your television switches off, the Pay TV Remote is successfully setup to control your television's power.

- *Some television's do not switch on pressing the* **Power** *button, please try pressing a "number" button to switch your television on.*
- *If your device does not respond, follow steps 1 through 6 for each Code listed for your device brand. If none of the Codes listed for your brand operate your device, then try the Search Method described on the next page, even if your brand is not listed at all.*
- *Some codes are quite similar. If your device does not respond or is not functioning properly with one of the Codes, try another Code listed under your brand.*

Setting the Code for your AMP / TUNER

Follow steps 1 – 6, changing Step 4 to:

4. Press and hold the **select** button, then press and hold the 8 button. Keep both buttons held down until the LED on the Pay TV Remote flashes twice

Setting the Code for your DVD / VCR

Follow steps 1 – 6, changing Step 4 to:

4. Press and hold the **select** button, then press and hold the 6 button. Keep both buttons held down until the LED on the Pay TV Remote flashes twice

Pay TV Remote Functions in AV mode

When in AV mode with a Device Code programmed into the Pay TV Remote the buttons perform the following functions

1. Power
  The Power button will operate the Power or Standby function on your programmed device
2. Play
  Switches the Pay TV Remote back to Pay TV mode and allows the Pay TV service to override any loop-through device and displays the Pay TV Guide.
3. tv guide
  Switches the Pay TV Remote back to Pay TV mode and allows the Pay TV service to override any loop-through device and displays the Pay TV active.
4. on demand
  Switches the Pay TV Remote back to Pay TV mode and allows the Pay TV service to override any loop-through device and displays the Pay TV Planner.
5. active
  Switches the Pay TV Remote back to Pay TV mode and allows the Pay TV service to override any loop-through device and displays the Pay TV Active menu.
6. i-Planner
  The setup button has no function and is therefore available for learning (see page 14).
7. i-Setup
  Provides the Menu function in DVD / VCR mode.
8. Menu
  Arrows, select and back
  These buttons are provided for Menu control in DVD / VCR mode.
  The Select button is provided to switch your television on
  If you cannot control your device properly, please continue the search Method, as you may be using the wrong code.
9. Volume +/-
  Change the volume on the programmed device (television or amp/tuner, depending on programmed device).
10. Channel +/-
  Change channel on the programmed device (television or VCR/DVD depending on programmed device).
11. mute
  Mutes the volume on the programmed devices (television or amp/tuner, depending on programmed device).
12. help
  Acts as an AV button does on your television's Remote Control, switches to AV mode and displays on the television
13. Transport buttons
  The REW, PAUSE (top part of key) / PLAY (bottom part of key), FF, REC and STOP keys operate the transport functions (PLAY, FF, REW etc.) of your DVD / VCR.
14. Number Buttons
  The Number buttons (0 - 9) change channel on the your television.
15. Colour Buttons
  Red: VCR input selection on amp/tuner.
  Green: DAT input selection on amp/tuner.
  Yellow: TV input selection on amp/tuner.
  Blue: Input select toggle feature on amp/tuner.

Search Procedure

If your device does not respond to the Pay TV Remote after you have tried all the Codes listed for your device brand, you may need to search for your Code. The search feature will work if your device brand is not listed at all. An alternative to this search procedure is to use the Pay TV Remote's learning capability described on the following pages of this Guide.

Searching the Code for Your Television

1. Switch your television on (not on standby).
2. Press and hold the **select** button on the Pay TV remote.
3. Press and hold the select button, then press and hold the red button. Keep both buttons held down until the LED on the Pay TV Remote flashes twice



4. Press the **av** button and release.
5. Now point the Pay TV Remote towards your television and press Power/Power Toggle.
6. If your television turns off press the **select** button to store the Code
7. If your television does not turn off, press the **av** button again, followed by the **Power** button. Keep alternating between the **av** and the **Power** buttons until your television set turns off.
  You may have to press these buttons many times (up to 180 times) so please be patient.
  As soon as your television turns off, press the **select** button to store the Code.

- *Some television's do not switch on when the Power button is pressed. Please try pressing a number button to switch your television on*
- *If you cannot control your device properly, please continue the search Method, as you may be using the wrong code.*

Searching the Code for your AMP / TUNER

Follow steps 1 – 8, only step 3 changes into;

Press and hold the **select** button then also press the 8 button (instead of **red** button) and keep both pressed until the LED (top front) shows two short (red) flashes.

Searching the Code for your DVD / VCR

Follow steps 1 – 8, changing step 3 to:

Press and hold the **select** button, then press and hold the 6 button. Keep both buttons held down until the LED on the Pay TV Remote flashes twice.

Identifying the Code programmed into the Pay TV Remote

Once you have set up the Code for your device, you can recall your device Code for future reference.

Example: Identifying your television Code

1. Press the av button on the Pay TV Remote.
2. Press and hold the **select** button, then press and hold the red button. Keep both buttons held down until the LED on the Pay TV Remote flashes twice.
3. Press **9 9 0** (The LED will flash twice).
4. For the first digit of your four-digit code, press **1** and count all the red flashes. If there are no flashes, the digit is "0".
5. For the second digit of your four-digit code, press **2** and count all the red flashes. If there are no flashes, the digit is "0".
6. For the third digit of your four-digit code, press **3** and count all the red flashes. If there are no flashes, the digit is "0".
7. For the fourth digit of your four-digit code, press **4** and count all the red flashes. If there are no flashes, the digit is "0".

Now you have your four-digit Code.

Identifying the AMP. / TUNER -Code programmed into the Pay for remote control

Follow steps 1 – 7, changing step 2 to:

Press and hold the **select** button, then press and hold the 8 button. Keep both buttons held down until the LED on the Pay TV Remote flashes twice

Identifying the DVD / VCR -Code programmed into the Pay TV remote control

Follow steps 1 – 7, changing step 2 to:

Press and hold the **select** button, then press and hold the 6 button. Keep both buttons held down until the LED on the Pay TV Remote flashes twice

Learning Feature

The Pay TV Remote offers a Learning Feature that allows you to copy almost any function from your original remote control onto the Pay TV Remote.

Please note that the Learning Feature is not possible when the Pay TV Remote Control is in Pay TV L mode. The av, Pay TV, tv guide, on demand, active and planner buttons can not have a function learnt onto them.

Before you start:

Make sure your original remote is working correctly.

Make sure the Pay TV Service is not displaying battery low indicator

Make sure you have the new Pay TV Remote, nor your original remote control is pointing at your device.

The Pay TV Remote can learn up to 20 functions.

Example: To copy the "Power" function from your original remote control onto the Power button on AV mode of the

Pay TV Remote:

1. Place the Pay TV Remote and your original remote control on a flat surface. Make sure the ends which you point at your device are facing each other. Keep the Remote Controls at a distance of 2 to 5cm (one to two inches).
2. Press the av button on the Pay TV Remote.
3. Press and hold the select button, then press and hold the red button. Keep both buttons held down until the LED on the Pay TV Remote flashes twice

4. Press **9 7 5** (the LED will flash twice).
5. Press and release the button on the where you want to place the learned function (e.g. **power** button). The LED will flash rapidly.
6. Press and hold the button on your original remote control that you want to copy (e.g. **power** button) until the LED on the Pay TV Remote flashes twice.
7. If you want to copy other functions repeat steps 5 and 6 pressing the next button you want to copy to learning.
8. To exit the learning mode, press and hold the select button until the LED flashes. The Pay TV Remote will also time-out of learning mode if no buttons are pressed for 10 seconds.

- *If you are having trouble learning a function that behaves as a toggle, in the function is turned on and off with the same button, for example the mute function, then as Step 6 rather than holding down the button on the original Remote Control try pressing and releasing it instead.*
- *If you have trouble using the learning feature please make sure you are away from direct sunlight or incandescent lights.*
- *If the remote has issues learning the function correctly then rotate the Pay TV remote 90 degrees to ensure alignment.*

Deleting a learned function

To delete a Learned Function from the Pay TV Remote, complete one of the following three options:

To delete a single learned function in AV mode

1. Press the av button on the Pay TV Remote.
2. Press and hold the select button, then press and hold the red button. Keep both buttons held down until the LED on the Pay TV Remote flashes twice.
3. Press **9 7 6** (the LED will flash twice).
4. Press the key containing the learned function. The LED will flash twice to indicate that the learned functions have been deleted. All learned buttons in AV mode will now revert to their original function.

To delete all learned functions and programmed Codes

1. Press the av button on the Pay TV Remote.
2. Press and hold the select button, then press and hold the red button. Keep both buttons held down until the LED on the Pay TV Remote flashes twice.
3. Press **9 8 8**.
4. The LED will flash twice to indicate that all the learned functions and any Codes have been deleted. All buttons in AV mode will now be disabled

Volume Allocation

The Pay TV Remote is able to be programmed so that, when in AV Mode, it will control the volume of the television or amplifier. When in Pay TV mode it will control the volume of the Pay TV. If both television and amplifier codes are programmed into the Pay TV Remote, it is possible to switch between which one the Pay TV Remote controls in AV mode for the mute buttons and volume. This function is called Volume Allocation.

When both television and amp/tuner codes have been programmed:

1. To switch to having the Pay TV Remote control the volume of your amp/tuner press and hold the select button then also press the 1
  The Pay TV Remote will now control the amp/tuner.
2. To switch to having the Pay TV Remote control the volume of your television press and hold the select button then also press the 2 button.
  The Pay TV Remote will now control the television.

Note: You must be in AV mode for this to function.

Volume Direct

The Volume Direct feature gives the volume +/- and mute buttons the same function when the Pay TV Remote is in Pay TV mode as when it is in AV mode.

1. Press the av button on the Pay TV Remote.
2. Press and hold the select button, then press and hold the red button. Keep both buttons held down until the LED on the Pay TV Remote flashes twice.
3. Press **9 9 3** (the LED will flash twice).

The Volume Direct feature is the default switch twice to indicate that Volume Direct feature has been set. The Pay TV Remote will now control the volume of your television even when the Pay TV Remote is in FOXTEL mode.

To reset the Volume Direct feature and have the volume buttons control the Pay TV, the following programming sequence needs to be performed.

1. Press the av button on the Pay TV 2 Remote.
2. Press and hold the select button, then press and hold the red button. Keep both buttons held down until the LED on the Pay TV Remote flashes twice.
3. Press **9 9 3** (the LED will flash twice).

The Volume Direct feature is now reset. The Pay TV Remote will now control the volume of the Pay TV when the Pay TV Remote is in Pay TV mode.

Learning Feature

The Pay TV Remote offers a Learning Feature that allows you to copy almost any function from your original remote control onto the Pay TV Remote.

Please note that the Learning Feature is not possible when the Pay TV Remote Control is in Pay TV L mode. The av, Pay TV, tv guide, on demand, active and planner buttons can not have a function learnt onto them.

Before you start:

Make sure your original remote is working correctly.

Make sure the Pay TV Service is not displaying battery low indicator

Make sure you have the new Pay TV Remote, nor your original remote control is pointing at your device.

The Pay TV Remote can learn up to 20 functions.

Example: To copy the "Power" function from your original remote control onto the Power button on AV mode of the

Pay TV Remote:

1. Place the Pay TV Remote and your original remote control on a flat surface. Make sure the ends which you point at your device are facing each other. Keep the Remote Controls at a distance of 2 to 5cm (one to two inches).
2. Press the av button on the Pay TV Remote.
3. Press and hold the select button, then press and hold the red button. Keep both buttons held down until the LED on the Pay TV Remote flashes twice

4. Press **9 7 5** (the LED will flash twice).
5. Press and release the button on the where you want to place the learned function (e.g. **power** button). The LED will flash rapidly.
6. Press and hold the button on your original remote control that you want to copy (e.g. **power** button) until the LED on the Pay TV Remote flashes twice.
7. If you want to copy other functions repeat steps 5 and 6 pressing the next button you want to copy to learning.
8. To exit the learning mode, press and hold the select button until the LED flashes. The Pay TV Remote will also time-out of learning mode if no buttons are pressed for 10 seconds.

Transport Key Direct

When you programme the Pay TV remote to control your VCR/DVD transport keys (play/pause, fast forward, rewind, stop and record) will control your VCR/DVD when the Pay TV Remote is in Pay TV mode (Pay TV L).

Should you be using a Pay TV remote in standard Pay TV set top unit you may wish to have the transport keys control your VCR/DVD when the Pay TV remote is in Pay TV mode. This is done with the Transport Key Direct functions. The Transport Key Direct features give the transport keys (play/pause, fast forward, rewind, stop and record) control your VCR/DVD when the Pay TV remote is in Pay TV mode as when it is in AV mode.

To activate the Transport Key Direct:

1. Press and hold the SELECT button, then press and hold the red button.
2. Press and hold the SELECT button, then press and hold the 9 button.
3. Press 9 9 5.
4. Press a play (the LED will flash twice).

To reset Transport Key Direct features and have transport buttons control the Pay TV, the following programming sequence needs to be performed.

1. Press the AV button on the Pay TV Remote.
2. Press and hold the SELECT button, then press and hold the red button. Keep both buttons held down until the LED on the Pay TV remote flashes twice.
3. Press 995.
4. Press stop (the LED will flash 4 times)

Power Allocation

When in AV Mode, the Pay TV Remote can be programmed to control the power of the television, amp/tuner or DVD/VCR. When in Pay TV mode it will control the power of the Pay TV. If both television and amp/tuner codes are programmed into the Pay TV Remote it is possible to switch between which one the Pay TV Remote when the power button is pressed. This function is called Power Allocation.

When both television and amp/tuner/DVD codes have been programmed:

1. To switch to having the Pay TV Remote control the power function of your VCR/DVD press and hold the select button then also press the 7 button.
2. To switch to having the Pay TV 2 Remote control the power function of your amp/tuner press and hold the select button then also press the 8 button.
3. To switch to having the Pay TV Remote control the power function of your television press and hold the select button then also press the 9 button.

Note: The power button is disabled until the LED on the Pay TV Remote flashes twice.

Power Direct

The Power Direct feature gives the power button of the Pay TV Remote the same function in Pay TV mode as when it is in AV mode.

1. Press the av button on the Pay TV Remote.
2. Press and hold the select button, then press and hold the red button. Keep both buttons held down until the LED on the Pay TV Remote flashes twice.
3. Press **9 9 6** (the LED will flash twice).

The Power Direct feature is the default switch twice to indicate that the Power Direct feature has been set. The Pay TV Remote will now control the power function of the Pay TV when the Pay TV Remote is in Pay TV mode.

To reset the Power Direct feature and have the power button control the Pay TV the following programming sequence needs to be performed.

1. Press the av button on the Pay TV Remote.
2. Press and hold the select button, then press and hold the red button. Keep both buttons held down until the LED on the Pay TV Remote flashes twice.
3. Press **9 9 6** (the LED will flash twice).

The Power Direct feature is now reset. The Pay TV Remote will now control the power function of the Pay TV when in FOXTEL mode.

POWER Macro

When in AV Mode, the Pay TV Remote is able to be programmed with codes that enable it to control the power of the television or amp/tuner or DVD/VCR. When in Pay TV mode it will control the power of the Pay TV. If more than one device code is programmed into the Pay TV Remote it is possible to switch between which one the Pay TV Remote controls in AV mode when the power button is pressed. This function is called Power Macro.

To activate the Power Macro:

1. Press and hold the select button, then press and hold the red button.
2. Press and hold the select button, then press and hold the 0 button.
3. Press 9 9 5.
4. Press the power button.
5. Press the av button.
6. Press each digit of the TV code.
7. When the Power Macro Power button sends the power function of all the codes programmed in the sequence of: television, amp/tuner, VCR/DVD.
  When more than one VCR/DVD codes have been programmed and the Power Macro feature has been enabled, the power button will send the power function of all the codes in the sequence of the power button. Should you wish to exclude a device from the Power function, perform the following steps:
  1. To exclude the Power Macro from controlling the power function of the television press and hold the select button then also press the 7 button.
  2. To exclude the Power Macro from controlling the power function of your amp/tuner press and hold the select button then also press the 8 button.
  3. To exclude the Power Macro from controlling the power function of your VCR/DVD press and hold the select button then also press the 9 button.
  4. To exclude the Power Macro from controlling the SELECT button press also press the 4 button?
  The Power Macro feature is not set, the <<Select + digit>> will perform power allocation.

Note: Power Macro can be used with Power Allocation to enable programmed devices to be excluded from the Power Macro. See Power Allocation in Pay TV mode.

To deactivate the Power Macro:

1. Press av button on the Pay TV Remote.
2. Press and hold the select button, then press and hold the red button. Keep both buttons held down until the LED on the Pay TV Remote flashes twice.
3. Press 9 9 5.
4. Press the power button again.

Hint: When using the Power Macro the on/off states of your devices can become unsynchronised, that is the television might be on but the amp/tuner is off. In this circumstance press the power button twice to turn the devices on. This is because on every press of the power button a toggle, the same command turns the device on as turns the device off. To overcome this, cover the front of the Pay TV Remote with your hand when it is sending to a device you don't want to change. The Power Macro first send the command to the television then the VCR/DVD then the amp/tuner. The three commands are sent about half a second apart.

FOXTEL Macro

When in AV mode, the Pay TV button on the Pay TV Remote can be programmed to initiate a series of commands before sending the FOXTEL command. This can be used to change an input of your television or HDMI switcher, or change another TV function, prior to entering Pay TV mode.

To activate the Pay TV Macro:

1. Press and hold the select button, then press and hold the red button.
2. Press and hold the select button, then press and hold the red button. Keep both buttons held down until the LED on the Pay TV Remote flashes twice.
3. Press 9 9 5.
4. Press the first command button you wish to use.
5. Press the second command button you wish to use.
6. Press the third command button you wish to use.
7. Press the fourth command button you wish to use.
8. Press select, the LED will flash twice.

When the Pay TV Macro is set and the Pay TV button (from av mode) will sends the programmed commands prior to the FOXTEL command.

To deactivate the Power Macro:

1. Press av button on the Pay TV Remote.
2. Press and hold the select button, then press and hold the red button. Keep both buttons held down until the LED on the Pay TV Remote flashes twice.
3. Press 9 9 5.
4. Press select, the LED will flash twice.

When Pay TV Macro is deactivated the Pay TV button (from av mode) it will return to the default single function mode.

Note:

Not all command buttons need to be used. i.e. you can use only 2 command buttons if desired.

Pay TV Macro can be used with Learning Functionality to control devices that are not in the code list of the Pay TV remote.

If a new Television Code is programmed into the Pay TV remote the, Pay TV macro will be deactivated.

Trouble-shooting

Problem	Possible Cause/ s	Solution
The FOXTEL i32 Remote is not working	Batteries are flat	Replace batteries.
	FOXTEL i32 Remote is damaged	Contact a representative from the place of purchase.
The LED flashes when the FOXTEL i32 Remote but there is no response from the FOXTEL i32	Line of Sight issue	Ensure that the path from the FOXTEL i32 Remote to any device is unobstructed in any way.
	FOXTEL i32 Remote is in AV Mode	Press the select button on the FOXTEL i32 Remote.
	FOXTEL i32 Remote is in FOXTEL Mode	FOXTEL Service not responding
The FOXTEL i32 Remote does not appear to work after pressing a button	FOXTEL i32 Remote is in FOXTEL Mode	Press the av button on the FOXTEL i32 Remote.
	Wrong Television Code used	Try another Television Code. Try the Learning Feature. Try the Code Search Feature.
The FOXTEL i32 Remote does not operate your Television	Batteries are flat	Replace batteries.
	Line of Sight issue	Ensure that the path from the FOXTEL i32 Remote to any device is not obstructed in any way.
The FOXTEL i32 Remote is not performing commands correctly	Wrong Television Code used	Try another Television Code. Try the Learning Feature. Try the Code Search Feature.
	FOXTEL i32 Remote is damaged	Contact a representative from the place of purchase.
	Batteries are flat	Replace batteries.
Original device Remote Control does not function	Original device Remote control faulty	Contact a representative from the place of purchase/ manufacturers

Problem	Possible Cause/ s	Solution
The Learning feature does not work	Original device Remote control faulty	Check that the batteries of the Remote control are not flat
	Incorrect steps followed	Contact a representative from the place of purchase/ manufacturer
	Line of Sight issue	Ensure that the path between the FOXTEL i32 Remote and device Remote control is not obstructed in any way
		Refer to the "Learning Feature" section of this guide to accomplish the steps

Television Codes

A.R. Systems 0065 0360 0364 0402
Abex 0065
Acoustic Research 1324
Acoustic Solutions 1723 1730 1731
Adcom 0245 0317
Admiral 0065
Adyson 0065
AIC 0065
Aiko 0065 0348
Aim 0065 0399 0246 0318
Aiwa 0065 0348 0377 0398 0318
Akai 0065 0399 0246 0318
Akiba 0065 0348
Akito 0065 0399 0246 0318
Alba 0065 0399 0246 0318
Alco 0065
Allorgan 0065 0377 0398 0318
Allstar 0065 0399 0246 0318
Alpha 0065 0399 0246 0318
Alpha Sonic 0065 0399 0246 0318
Alphatronic 0065 0399 0246 0318
Amstrad 0065 0399 0246 0318
Anam 0065 0399 0246 0318
Anam National 0065
Anderson 0065
Ansonic 0065
Antares 0065
Archer Marine 0065
Arcon 0065
Arena 0065
Ariston 0065
Arthur Martin 0065
Asa 0065
Asberg 0065
Asha 0065
Asora 0065
Aspes 0065
Aspy 0065
Astar 0065
Asuka 0065
Atlantic 0065
Atori 0065
Audio Dynamic 0065
Audiosonic 0065
Audiotech 0065
Audiovox 0479
Augustav 0065
Autotech 0065
AWA 0065
Axion 0065
Baird 0065
Bang & Olufsen 0065
Barco 0065
Basic 0065
Basic Line 0065
Bauer 0065
Baumann Hoyer 0065
Bazin 0065
Beko 0065
Bell & Howell 0065
Bellini 0065
Benjamin 0065
Bentley 0065
Berkeley 0065
Bestar 0065
Bestar Siemens 0065
Best Mark 0065
Best Channel 0065
Black Panther 0065
Black Star 0065
Blaupunkt 0065
Blue Sky 0065
Bluesonic 0065
Blue Star 0065
Bondstec 0065
Boots 0065
Bosch 0065
Boston 0065
Brandt 0065
Brimtech 0065
Brinkmann 0065
Brionvega 0065
Britannia 0065
Brokaw 0065
Brother 0065
Brum 0065
BSR 0065
Bush 0065
Cairn 0065
Calaron 0065
Calcomp 0065
Calix 0065
Calypso 0065
Camtron 0065
Canadian Content 0065
Canal Digital 0065
Canal Satellite 0065
Canon 0065
Capehart 0065
Carad 0065
Carena 0065
Carlton 0065
Carrera 0065
Carver 0065
Cascade 0065
Casio 0065
Cat 0065
Cathay 0065
CCE 0065
Celesteel 0065
Celtic 0065
Centrex 0065
Century 0065
CGE 0065
Centurion 0065
Centurion 0065
Century 0065
Cetec 0065
Chambers 0065
Changhong 0065
Channel Master 0065
Chiaro 0065
Chimei 0065
Chinon 0065
Christian 0065
Cimline 0065
Cineral 0065
Citizen 0065
Clarion 0065
CMS Satplex 0065
Colortech 0065
Concorde 0065
Condor 0065
Contec 0065
Contec 0065
Continental 0065
Cony 0065
Cosmos 0065
Craig 0065
Crosley 0065
Crown 0065
Crystal 0065
CS Electronics 0065
CTC 0065
Cub 0065
Curtis Mathes 0065
Cybernex 0065
Cytron 0065
Daewoo 0065
Dainichi 0065
Daitsu 0065
Dansai 0065
Dantax 0065
Datsun 0065
Dawa 0065
Dayton 0065
Decca 0065
De Graaf 0065
DEC 0065
Denco 0065
Dentron 0065
Denver 0065
Desmet 0065
Diamant 0065
Diamond 0065
Dimas 0065
Dimtron 0065
Dinamic 0065
Dixi 0065
Dixon 0065
DNTSCH 0065
DSE 0065
Dual 0065
Dumont 0065
Dunhill 0065
Durabrand 0065
Dux 0065
Dynatron 0065
Dynatronic 0065
Dynavox 0065
Dynex 0065
Eagle 0065
Eaton 0065
Ecko 0065
Edelbrock 0065
Edenwood 0065
Edison 0065
Elbe 0065
Elbe Sky 0065
Elbe Star 0065
Elbe Sun 0065
Elbe Tech 0065
Elbe Tele 0065
Elbe Tone 0065
Elbe Vision 0065
Elbe Vox 0065
Elbe Way 0065
Elbe Wave 0065
Elbe Wire 0065
Elbe Wise 0065
Elbe Wish 0065
Elbe Wit 0065
Elbe Wix 0065
Elbe Wiz 0065
Elbe Wizz 0065
Elbe Wizzy 0065
Elbe Wizzz 0065
Elbe Wizzzy 0065
Elbe Wizzzz 0065
Elbe Wizzzzy 0065
Elbe Wizzzzz 0065
Elbe Wizzzzzy 0065
Elbe Wizzzzzz 0065
Elbe Wizzzzzzy 0065
Elbe Wizzzzzzz 0065
Elbe Wizzzzzzzy 0065
Elbe Wizzzzzzzz 0065
Elbe Wizzzzzzzzy 0065
Elbe Wizzzzzzzzz 0065
Elbe Wizzzzzzzzzy 0065
Elbe Wizzzzzzzzzz 0065
Elbe Wizzzzzzzzzzy 0065
Elbe Wizzzzzzzzzzz 0065
Elbe Wizzzzzzzzzzzy 0065
Elbe Wizzzzzzzzzzzz 0065
Elbe Wizzzzzzzzzzzzy 0065
Elbe Wizzzzzzzzzzzzz 0065
Elbe Wizzzzzzzzzzzzzy 0065
Elbe Wizzzzzzzzzzzzzz 0065
Elbe Wizzzzzzzzzzzzzzy 0065
Elbe Wizzzzzzzzzzzzzzz 0065
Elbe Wizzzzzzzzzzzzzzzy 0065
Elbe Wizzzzzzzzzzzzzzzz 0065
Elbe Wizzzzzzzzzzzzzzzzy 0065
Elbe Wizzzzzzzzzzzzzzzzz 0065
Elbe Wizzzzzzzzzzzzzzzzzy 0065
Elbe Wizzzzzzzzzzzzzzzzzz 0065
Elbe Wizzzzzzzzzzzzzzzzzzy 0065
Elbe Wizzzzzzzzzzzzzzzzzzz 0065
Elbe Wizzzzzzzzzzzzzzzzzzzy 0065
Elbe Wizzzzzzzzzzzzzzzzzzzz 0065
Elbe Wizzzzzzzzzzzzzzzzzzzzy 0065
Elbe Wizzzzzzzzzzzzzzzzzzzzz 0065
Elbe Wizzzzzzzzzzzzzzzzzzzzzy 0065
Elbe Wizzzzzzzzzzzzzzzzzzzzzz 0065
Elbe Wizzzzzzzzzzzzzzzzzzzzzzy 0065
Elbe Wizzzzzzzzzzzzzzzzzzzzzzz 0065
Elbe Wizzzzzzzzzzzzzzzzzz