POWERTECH

12V 5W Solar Folding Bag Charger

With USB Charging Port

MB-3649



User Manual

Specifications:

Panel: Monocrystalline solar panel

Power Tolerance: +/-5%

Maximum Power: 5W

Voltage at Pmax (Vmp): 17.4V

Current at Pmax (Imp): 0.29A

Open Circuit Voltage (Voc): 21.6V

Short Circuit Current (Isc): 0.32A

USB Output Power: 400mA max

USB Output Voltage: 5V

Dimensions: 190(L) folded - 610(L) extended x 175(H) x 42(D) mm


Operating Instructions:

- Unfold the solar charger and peel the screen cover off the solar panel.
- Place the panel at a position that can receive direct sunlight and avoid shadows covering any part of the solar cells in the panel.
- Tilt the solar panel at a suitable angle to increase efficiency.
- Make sure the power indicator light comes on before connecting any devices to the charger.

Features:

- Built in USB port to charge smartphones, tablets and other USB devices.
- 12V power port to power 12V devices or recharging 12 batteries.
- This unit has a chain port connection allows you to "daisy chain" up to 3 panels together in parallel to be able to power 12V devices with higher power consumption or charge bigger size batteries.

Diagram:



Accessories:



1 x Daisy Chain lead



1 x Cigarette lighter socket lead

Troubleshooting:

If your solar panel is not working properly, please go through the following instructions for quick troubleshooting:

- Make sure the solar panel is facing direct sunlight.
- Make sure the connections are connected properly.
- Make sure the devices charging with this solar panel are compatible with the output voltages and correct polarity.
- Cloudy or rainy weather conditions might reduce the efficiency of this product

NOTES:

- Do not get any part of the unit or its accessories wet.
- Do not attempt to open, modify or repair any part of the unit or its accessories.
- Please use this product in a well ventilated area.

Distributed by: TechBrands Electus Distribution Pty. Ltd. 320 Victoria Rd, Rydalmere NSW 2116 Australia Ph: 1300 738 555

> Int'l: +61 2 8832 3200 Fax: 1300 738 500 www.techbrands.com