NEXTECH



Wire-Free Wi-Fi

Battery Camera

QC3890

User Manual

	What is in the Bo	K?
		100 M
Battery Camera	Iron Ball Wall Mount	Screw Sets
WHD" WHAT WE AND A WHIT		Smart WIFI Battery Camera Quick User Guide
Double sided adhesive	USB Cable	Quick User Guide

1x camera, 1x wall mount, 1x screws

1x Double-sided adhesive

1x USB cable, 1x Quick User Guide

Product Details





1. Install Smartlife APP

2.1 Download APP smartlife from googleplay or apple store.



2.2 Register account and login

- 2.2.1 Select Country
- 2.2.2 Input mobile phone number or Email
- 2.2.3 Set password
- 2.2.4 Login with new account and password

4. Add Device

4.1 Insert micro SD card

Please insert a micro SD card to record videos when motion detected and playback. (card not included, supports 128GB Max.)

* NOTE: Please insert the SD card before power on, otherwise, the SD Card cannot be read.

4.2 Power on the camera

Press and hold on the top Power Button for 5 seconds to Turn on Camera (if can not power on, please plug in DC5V 1A/2A phone adapter to charge 15min first). Power adapter is not included in packing list.



NOTE: Ensure the indicator light slowly blinking in RED before setup WiFi

4.3 Setup Wi-Fi

4.3.1 Bring the camera and phone to the router within 1 to 3 feet (30 to 100 cm) and connect wifi.



NOTE: Please note camera only works under 2.4G Wi-Fi, not supports 5G Wi-Fi.

4.3.2 Run Smartlife App, select "Security & Sensor" ---"Smart Camera"

- 4.3.3 Add Device
- 4.3.4 Enter Wi-Fi Password
- 4.3.5 Scan with the Camera





<

🛪 📺, No SIM 🗢

<

23:54 Add Device

Add Device

Scan with the camera

When you tap CONTINUE, the mobile phone displays a QR code. Hold the camera 15 to 20 cm in front of the mobile phone for the camera to scan the QR code.





Heard nothing at all

Heard the beep

No SIN	A 🗢 20:27 → 📼 Add Device	No SIM 奈 Davis ∽	20:41	⊲ ■ 0 +
		C	Welcome home Set your home location, get more in	formation >
	Connecting	All devices	Living Room Bedroom	Secor ····
Make sure your router, mobile, and device are as close as possible	Make sure your router, mobile, and device are as close as possible		Battery Camera Online	
	40%			
	Device found Register device to the smart cloud Initializing device			
		Home	-Ò- Smart	O Me

5. Camera Menu

No SIM 穼	21:03	7	No SIM 🗢	20:48	7	—),
< 1	Battery Camera	2 🗹	< :	Settings		
2019-05-14 21:03:33		Signal: 100%	Device Name	14	Battery Camera	
			Share Device	15		>
			Device Information	16		>
			Power management settir	ng 17		>
	<mark>8</mark> □ • 60 %		Basic function settings	18		>
			PIR on/off switch	19	Medium	
ſÕſ	Q		Value-added Service Pure	chase 20		>
Screenshot	Speak	Record	Memory card settings	21		>
9	10	11	Feedback	22		>
12	13		Firmware information	23		>
(>,				24		
Playback	Cloud storage		Ren	24 nove Device		

APP Menu	Camera Settings options
1. Camera Name	13. Cloud Storage
2. Camera Settings	14. Device Name
3. Camera Time	15. Share Device
4. Network Signal strength	16. Device Information
5. Audio	17. Power Management Setting
6. HD/SD	18. Basic function settings
7. Full Screen	19. PIR on.off switch
8. Battery Volume	20. Value-added Service Purchase
9. Screenshot	21. Memory card Settings
10. Speak	22. Feedback
11. Record	23. Firmware information
12. Playback	24. Remove Device

6. Share Video to Friend

6.1. Add your Friend's account in app

NOTE: Firstly ensure Friend's account already registered in Smartlife app

6.2 Share video to your Friend's account



7. Alarm Push Notification and playback

Battery camera with PIR sensor is not designed for 7X24 all day recording, but just push alarm message notification to phone app and record video to SD card when PIR sensor detected human body motion events, then you can playback the motion videos wherever you are via Smartlife App. When PIR is triggered, camera and system actions:

1. Alarm Sound in app (please enable Smartlife app notification in mobile setting and also mobile volume is on)

2. Alarm Message Notification (please enable Smartlife app notification in mobile setting)

3. Alarm snapshot and video record on SD card (please insert SD Card)



8. Camera Installation

8.1. You can put it on any flat place: table, chair, floor, etc. 8.2 Install with Wall Mount:

8.3 A3 Wall Mount Installation

Fix the iron ball bracket to the wall with screws or double-sided adhesive, and then magnetize the camera to the iron ball. Installation is very convenient and also easy to adjust the angle.



9. To reduce false alarms, please note that:

- Do not install the camera facing any objects with bright lights, including sunshine, bright lamp lights, etc.
- Do not place the camera too close to a place where there frequently moving vehicles. Based on numerous tests, the recommended distance between the camera and vehicle is 15 meters (55ft).
- Stay away from the outlets, including air conditioner vents, humidifier outlets, the heat transfer vents of the projectors, etc.
- Do not install the camera facing the mirror.
- Keep the camera at least 1 meter away from any wireless devices, including Wi-Fi routers and phones, in order to avoid wireless interference.

Appendix:

LED Status Description

No.	LED Status	Camera Status
1	Slow blinking Red	Awaiting WiFi Connection
2	Fast blinking Red	WiFi Connecting
3	Solid on Red	Network is abnormal
4	Solid on Blue	WiFi Connected

Trouble Shooting Sheet

No.	Description	Solution and operation
1	Unable to connect	 Check your WiFi name and password Ensure your WiFi is 2.4G, not support 5G Ensure your camera and phone close to router
2	Reset	 Press and hold the reset button for 5 seconds Hear one "bugu" sound Red light turns to slow blinking
3	Change to a new Network	 Press reset key to factory default setting Re-connection
4	Failed to add Device	Please enable Smartlife app cellular data on in mobile settings
5	No Alarm Push	Please enable Smartlife app notification in mobile settings
6	No Alarm Video Record	Please insert SD Card

Distributed by: Electus Distribution Pty. Ltd. 320 Victoria Rd, Rydalmere NSW 2116 Australia www.electusdistribution.com.au Made in China