17Watt DIMMABLE LED DRIVER 220-240VAC / 24VDC, 700mA Constant Current Switch Mode Power Supply



Introduction

This electronic LED Driver is a compact, constant current power supply which is internally stabilized with high quality electronics. This unit has been specially developed to operate the Ecolume DL90 series Downlights with a Clipsal Trailing Edge Dimmer.

Electrical Characteristics

Primary rated input voltage 240Vac +/-10% 50Hz

Rated input Current < 100mA Standby power < 0. 3W

Power Factor >0.9 (without dimmer)

Input Fuse ProtectionFuse glass Slow blow 250V 2ALED driving voltage12V ~ 24Vdc (4 ~ 6 LEDs)Output current700mA +/-5% (without dimmer)Output voltage ripple<1.5V @ 240Vac input (without dimmer)</td>Efficiency>78% @ 240Vac input (without dimmer)

Start up delay

<1S @ 240Vac input & full load

<3S @ 240Vac input & minimum load

Hold up time

>10mS @ 240Vac input & full load

Insulation Resistance >50M ohm @500Vdc

Di-electrical Strength 3KVac for 60 second Leakage <5mA

Protection

Short Circuit Protection Hiccup (auto-restart after SC removed)
Over Load Protection Current limited to Io<700mA rms
Over shoot Protection Not over 10% output voltage

Environment

Operating Temperature -10°C to +50°C
Storage Temperature -25°C to +85°C
Cooling Convection only

Relative Humidity 5% to 95% (non-condensing)

MTBF >350,000Hrs @ 25°C (MIL217F parts count method)

Case Size 144x33x50mm (LxHxW)

Unit weight 130gms

Approvals

 Safety
 Certified to AS/NZS61347-1, EN61347-1, IEC61347.2.13, IEC61347-1

 EMC
 Meets requirements of EN61000.3.2, EN55015, EN61547



Features

Dimmable with Clipsal trailing edge dimmer Constant current output Large, protected terminals Rugged and easy to handle Lightweight Low power supply losses Mounting Lugs 3 Year warranty

Soanar

Level 1, 39 Hewish Road, Croydon Victoria 3136

Ph. Toll Free - AUS: 1300 762 627 - NZ: 0508 765 956

Web: www.soanar.com